

**AUTOMATIC GAIN CONTROL WITH DIGITAL FILTERING FOR
RADIO-FREQUENCY COMMUNICATIONS SYSTEMS**

5 BACKGROUND OF THE INVENTION

 The present invention relates generally to
automatic gain control (AGC) for use in radio-frequency
(RF) communications systems. More specifically, but
without limitation thereto, the present invention
10 relates to an automatic gain control with digital
filtering for mitigating dynamic range reduction due to
out-of-band interference.

 Typical radio frequency communications
signals are divided into a number of channels within a
15 signal band centered around a carrier frequency. For
example, 10 channels each 5 megahertz (MHz) wide can
fit into a 50 MHz wide frequency band centered at a
carrier frequency of, for example, 2 gigahertz (GHz).
About 99% of the signal in each channel is contained in
20 a band of frequencies about 4.4 MHz wide, ordinarily
leaving a gap between adjacent channels to avoid mutual
interference. During transmission of the signal,
however, signal from one channel may cross over into
other channels (or bands) causing out-of-band
25 interference. Much time, effort, and ingenuity has
been devoted to the problem of filtering out this out-
of-band interference.

 One of the difficulties encountered in signal
filtering is that radio frequency signals in the
30 gigahertz range are much more difficult to filter than
signals at lower frequencies. One approach to solving
this filtering problem is to translate the radio
frequency signal to an intermediate frequency (IF)
signal. For example, if a 5 MHz channel is transmitted
35 on a carrier in the gigahertz range from 1.995 GHz to
2.000GHz, the carrier may be translated to an

0000207 6646960

5 Analog filters in the radio frequency,
intermediate frequency, and baseband ranges are
typically used to mitigate out-of-band interference.
Disadvantageously, analog filters can be expensive,
especially for the higher frequencies.

10

15

20

30

35

FIG. 6 illustrates frequency response comparisons as between an "ideal" IF filter and a "practical" IF filter.

090399 102000

10 In one embodiment, the invention may be characterized as an automatic gain control that includes a digital lowpass filter for filtering a series of digital samples generated by an analog-to-digital converter to generate a lowpass filtered
15 digital sample series; a power averager coupled to the digital lowpass filter for calculating an average power of the lowpass filtered digital sample series; and a lookup table coupled to the power averager for setting the selectable gain of an amplifier coupled to the
20 analog-to-digital converter as a function of the average power.

The antenna 102 receives as input a radio frequency signal containing the signal channels. The radio frequency signal may be transmitted from any source of radio frequency signals, for example, a

000001 662E960

satellite antenna. The radio frequency filter 104 removes a portion of out-of-band interference from the received radio frequency signal. The intermediate frequency converter 106 converts or translates the
5 relatively high frequency radio frequency signal to a more readily filtered, lower intermediate frequency signal. The intermediate frequency filter 108A removes harmonics from the intermediate frequency converter 106 and more of the out-of-band interference from the
10 intermediate frequency signal. The intermediate frequency amplifier 110 amplifies the filtered intermediate frequency signal. The demodulator 114 translates the amplified intermediate frequency signal to a complex baseband signal. The complex baseband
15 signal is illustrated by double lines, one for the in-phase or real component, and the other for the quadrature-phase or imaginary component.

The analog-to-digital converter 118 samples the complex baseband signal at a rate greater than the
20 Nyquist rate to avoid aliasing and converts the complex baseband signal to complex digital samples, i.e., two separate series of digital samples that are representative of the real (in-phase) and imaginary (quadrature-phase) components of the communications
25 signal respectively. The two series of digital samples output by the analog-to-digital converter 118 are then received as input by the digital receiver 120.

The conventional automatic gain control circuit 112 estimates the power of the communications
30 signal from the digital samples and periodically adjusts the gain of the intermediate frequency amplifier 110 so that the amplified intermediate frequency signal is scaled to the dynamic range of the analog-to-digital converter 118. The purpose of
35 scaling the intermediate frequency signal to the

dynamic range of the analog-to-digital converter 118 is to maximize the signal-to-noise ratio at the input of the digital receiver 120. A disadvantage of this approach is that out-of-band interference, if not
5 adequately mitigated by the analog filters 104, 108, and 116, may reduce the available gain of the intermediate frequency amplifier 110. The available gain of the intermediate frequency amplifier 110 is reduced when the out-of-band interference generates peak
10 amplitudes that must be accommodated by the dynamic range of the analog-to-digital converter to avoid clipping, leaving fewer bits of dynamic range for the communications signal. The reduced gain of the intermediate frequency amplifier 110 reduces the
15 dynamic range of the communications signal at the analog-to-digital converter 118 and correspondingly the signal-to-noise ratio (SNR) at the input of the digital receiver 120. Out-of-band interference is especially common in multiple access systems because adjacent
20 frequency bands are used concurrently. A solution to the problem of out-of-band interference is to improve the analog filters, but high-performance analog filters may be prohibitively expensive.

FIG. 2 is a block diagram of a radio
25 frequency communications receiver 200 using digitally filtered automatic gain control. By introducing digital filtering into the automatic gain control, the requirements for the analog filters may be relaxed, substantially lowering the cost of the radio frequency
30 communications receiver 200. Alternatively, the out-of-band interference may be further reduced for the same analog filters, further increasing the signal-to-noise ratio at the digital receiver 120.

Shown in FIG. 2 are an antenna 102, a radio
35 frequency filter circuit 104, an intermediate frequency

000201 662E660

converter 106, an intermediate frequency (IF) filter 108B, herein a "practical" IF filter embodiment, an intermediate frequency amplifier 110, a filtered automatic gain control 202, a demodulator 114, an analog-to-digital (A/D) converter 118, a digital receiver 120, and a finite impulse response lowpass filter 122.

The automatic gain control 202 includes a first decimator 204, a digital infinite impulse response filter 206, a second decimator 208, an average power estimator 210, and a gain look-up table 212.

In operation, the radio frequency communications receiver 200 is similar to that of FIG. 1 except as follows. The analog-to-digital converter 118 samples the filtered complex baseband signal to provide an adequate sampling output for the digital finite impulse response filter 122 at a sampling rate of, for example, four times the Nyquist sampling rate. The analog-to-digital converter 118 digitizes the complex baseband signal to a series of complex digital samples, i.e., two separate series of digital samples that are representative of the real (in-phase) and imaginary (quadrature-phase) components of the communications signal respectively. The two series of digital samples output by the analog-to-digital converter 118 are then received as input by the digital finite impulse response lowpass filter 122. The digital finite impulse response lowpass filter 122 further removes out-of-band interference and outputs a digital output signal to the digital receiver 120. The digital finite impulse response lowpass filter 122 and the digital receiver 120 may be implemented in hardware or software according to well known techniques.

The filtered automatic gain control 202 receives as input the two series of digital samples from the analog-to-digital converter 118. Assuming

000001" 667E960

that the front-end analog filters have sufficiently removed interference at frequencies higher than the Nyquist rate, the two series of digital samples may be decimated by a factor of two by the first decimator 204 without risk of aliasing. By reducing the sample rate by half, the first decimator 204 relaxes the performance required of the digital infinite impulse response filter 206.

The digital infinite impulse response filter 206 attenuates out-of-band interference between half the Nyquist rate and the Nyquist rate from the decimated digital samples output by the first decimator 204. The digital infinite impulse response filter 206 in this example has the desirable characteristics of simple implementation and minimal delay, however other types of filters may be used to remove frequencies between half the Nyquist rate and the Nyquist rate to suit specific applications.

The second decimator 208 again reduces the sample rate by half to relax the performance requirements of the average power estimator 210. The average power estimator calculates an average power estimate as a running average of the signal power, for example, by calculating a sum of the squares of the two series of digital samples received from the second decimator 208. The average power estimate is generated as output to the lookup table 212.

The lookup table 212 contains amplifier gain coefficients for each average power estimate. The amplifier gain coefficients are precalculated as a function of the average power estimate, for example, the scalar factor between each average power estimate and the desired average output power within the dynamic range of the analog-to-digital converter 118. Each amplifier gain coefficient adjusts the gain of the

000001" 667E6960

060979 J06000

FIG. 3 is a block diagram of an infinite impulse response filter 206 for the automatic gain control of FIG. 2 that can provide 20 dB attenuation between 0.8 of the Nyquist rate and 1.0 of the Nyquist rate. Identical infinite impulse response filters 206 may be used for each of the two series of digital samples. While the digital finite impulse response lowpass filter 122 is used for baseband filtering at the digital receiver 120 because of its low phase and magnitude distortion in the filtered digital baseband, the digital infinite impulse response lowpass filter 206 is a preferred choice for the filtered automatic

By way of example, for code division multiple access (CDMA) applications requiring compliance with the CDMA2000 standard in which each channel has, for example, a bandwidth of 3.6864 MHz, the infinite impulse response filter 206 may be described by the following transfer function:

The transfer function (1) may be implemented in either hardware or software as shown in FIG. 3 by a first sum function 302, a first sum register 304, a first unit delay 306, a third sum function 308, a second unit delay 310, a first multiplier 312, a second multiplier 314, a second sum function 316, a second sum register 318, a third sum register 320, and a third multiplier 322.

In operation, the output of the first decimator 204 is received as an N-bit wide input and summed by the first sum function 302. The output of the sum function 302 is stored in the first sum
30 register 304. The first sum register 304 is N+1 bits wide, which is one bit wider than the output of the analog-to-digital converter 118, to accommodate the output of the first sum function 302.

The output of the first sum register 304 is delayed one sample period by the first unit delay 306 to generate a first delayed sum.

The first delayed sum output from the first
5 unit delay 306 is multiplied by two by the first
multiplier 312 and is delayed one sample period by the
second unit delay 310 to generate a second delayed sum.
The second delayed sum is multiplied by -0.25 by the
second multiplier 314. The output of the second
10 multiplier 314 is summed by the first sum function 302.
The second delayed sum and the output of the first
multiplier 312 are summed by the second sum function
316.

The output of the second sum function 316 is
15 stored in the second sum register 318. The second sum
register 318 is one bit wider than the output of the
analog-to-digital converter 118 to accommodate the
output of the second sum function 316. The output of
the second sum register 318 and the output of the first
20 sum register 304 are summed by the third sum function
308. The output of the third sum function 308 is
stored in the third sum register 320. The third sum
register 320 is two bits wider than the output of the
analog-to-digital converter 118 to accommodate the
25 output of the third sum function 308.

The output of the third sum register 320 is
multiplied by 0.3125 by the third multiplier 322 to
normalize the output of the third multiplier 322 to the
digital sample series received as input by the first
30 sum function 302. The output of the third multiplier
322 has the same number of bits N as the analog-to-
digital converter 118 and is the lowpass filtered
output of the infinite impulse response lowpass filter
206.

000201" 662E960

Figs. 4 and 5 are graphs of the magnitude response and phase response versus frequency, respectively, of the infinite impulse response filter 206 shown in Fig.3. Truncation effects at the output of the third multiplier 322 from normalizing the output to the input without rounding off the least significant bit are minimal when applied to an AGC circuit. Accordingly, Fig. 6 is a graph showing the frequency response comparisons as between the "ideal" IF filter 108A of Fig. 1 and that of the "practical" IF filter 108B frequency response of Fig. 2. A magnitude response of 10 dB or more is illustrated.

For a channel having a bandwidth of 3.68 MHz (i.e.; centered at zero extending to band edges at - 1.84 MHz and +1.84MHz) attenuation at the band edge (1.84MHz) is 1.5 dB, while at 3.2MHz attenuation is 26.5dB. Because the filter passband is not entirely flat, the 8-bit output power is 0.046 dB above the unfiltered power for a code division multiple access (CDMA) signal. The lookup table 212 can be modified accordingly to compensate for this discrepancy.

Other modifications, variations, and arrangements of the present invention may be made in accordance with the above teachings other than as specifically described to practice the invention within the spirit and scope defined by the following claims.